FISHMAN FLUENCE™

Classic Open Core Humbucker Set
Custom Setup - 1
5-Way Super Switch

Neck: Classic Neck
Open Core

Bridge: Classic Bridge
Open Core

9V Battery

(+)

(-)

Ring

Sleeve

Output
Jack

Tip

Bridge
Ground

Volume

25k

25k

.22uF

Tone
Pull for Voice-2
Positions 1 & 5

Pickup Selector
5-Position
4P5T Rotary SuperSwitch

Pickup Selector Function

1. Bridge Humbucker (Voice-1 or 2 Selectable)
2. Bridge (Inner Coil)
3. Bridge & Neck (Inner Coils)
4. Neck (Inner Coil)
5. Neck Humbucker (Voice-1 or 2 Selectable)